

尺寸 DIMENSION

型号MODEL	A	B
MPA 184E	432	147
MPA 184F	522	237
MPA 184G	522	237

注：表中A.B为SAE4 & SAE5时的长度尺寸

SAE2 尺寸A.B需增加39

SAE3 尺寸A.B需增加12

SAE6 尺寸A.B需增加31.7

SAE3 & SAE 4的8个孔分布于12等分圆周上

Remark: In the table A&B refers to the length of SAE 4& SAE 5

The length of SAE 2(A.B) should add 39

The length of SAE 3(A.B) should add 12

The length of SAE 6(A.B) should add 31.7

The length of SAE 3& SAE 4 are distributed in the 12 equal parts of circumference

法兰式过渡接套 FLANGE

S.A.E.NO.	R	S	T	U	W	X	C
2	12	11	466.7	15	447.5	489	172
3	8	11	428.6	15	409.5	451	145
4	8	11	381.0	15	361.9	402	133
5	8	11	333.3	22.5	314.3	356	133
6	8	11	285.8	22.5	266.7	308	164.7

盘式联轴器 DISC COUPLING

S. A. E. NO.	AN	AR	AS	AT	V
6.5	30.16	6	8.7	200.0	215.8
7.5	30.16	8	8.7	222.2	241.2
8	61.9	6	11	244.5	263.4
10	53.98	8	11	295.3	314.2
11.5	39.58	8	11	333.4	352.3

Outline for MPA 184 E-G (Single-bearing)

